

## DEUTSCH

### Einbauanleitung




Figure 1




Figure 2

Figure 3

Overload LED	DC OK LED	DC OK Contact
Normal mode	OFF	ON
During Power Boost	OFF	ON
Overload ( $V_{out} > 90\%$ )	Flashing	OFF
Output short circuit	Flashing	Open
Temperature shut down	Flashing	OFF
No input power	OFF	OFF

Figure 4




Figure 5




Figure 6

### Power Derating Curve for PSU




Figure 7

## DEUTSCH

## DEUTSCH

### Technische Daten

#### Eingangskennwerte (AC)

Nennspannung en frequente	100-240 Vac / 50-60 Hz; oder 110-300 Vdc (nur für ITE)
Spannungsbereich	85-276 Vac (DC-Eingangsspannungsbereich 88-375 Vdc)
Frequenzbereich	47-63 Hz
Nennstrom	< 5.27 A bei 100 Vac, < 2.48 A bei 230 Vac < 5.00 A bei 110 Vdc, < 3.00 A bei 300 Vdc
Einschaltstrombegrenzung Pt (+25 °C, Kaltstart)	9 A typ. bei 120 Vac, 7 A typ. bei 230 Vac
Netzausfallüberbrückung bei Nennlast	32 ms typ. bei 120 Vac & 230 Vac
Einschaltzeit	610 ms typ. bei 120 Vac, 660 ms typ. bei 230 Vac
Interne Sicherung	T 8 A - LITTELFUSE (Type 477) UL E2636: Rated 500 Vac and 500 Vdc Europe: Rated 500 Vac and 500 Vdc
Ableitstrom	0.58 mA typ. bei 230 Vac
Ausgangskennwerte (DC)	
Nennausgangsspannung $U_{out}$	24 Vdc
Werkseinstellung	24.05-24.15 Vdc
Einstellbereich der Ausgangsspannung	24-28 Vdc
Ausgangstrom	20 A ( $V_{out} = 24$ Vdc) 17 A ( $V_{out} = 28$ Vdc) 30 A (für 5 s, $V_{out} = 24$ Vdc) 25.5 A (für 5 s, $V_{out} = 28$ Vdc)
Derating (Leistungsherabsetzung)	> 60 °C (2.5 % / °C) Vertikal > 40 °C (2.5 % / °C) Horizontal
Anlaufen bei Kapazitiven Lasten	20.000 µF typ.
Max. Verlustleistung Leerlauf/Nennlast	10 W / 31.4 W
Wirkungsgrad bei 100 % Last	92.4 % typ. bei 120 Vac, 93.9 % typ. bei 230 Vac
PARD (20 MHz) bei 100 % Last	< 100mVpp
Max. Relaischaltleistung	30 V (SELV) / 1 A Wirklast
Parallelschaltbarkeit	DRR-40□
Allgemeine Kennwerte	
Gehäusetyp	Aluminum
LED-Signale	Grüne LED „DC OK“ Rot LED „Overload“
MTBF (mittlere Betriebszeit zwischen Ausfällen)	> 778.800 Std., entsprechend Telcordia SR-332 (IP: 100 Vac; O/P: 24 V, 20 A; Ta: 25 °C)
Abmessungen (B x H x T)	124 mm x 82 mm x 117 mm
Gewicht	1.4 kg
Art der Anschlussklemme	Schraubanschluss
Abisolierlänge	7 mm
Betriebstemperaturbereich (Umgebungstemperatur)	-25 °C bis +70 °C (Leistungsherabsetzung gemäß Abb. 7)
Lagertemperaturbereich	-40 °C bis +85 °C
Luftfeuchte bei +25 °C, keine Belaufung	5 bis 95 % relative Luftfeuchte
Vibration (außer Betrieb)	10 bis 500 Hz, Besch. 30 m/s², 0.35 mm Erschütterungsamplitude (3 G max.) für 60 min. in X, Y & Z Richtung, gemäß IEC60068-2-6
Stoßfestigkeit (in alle Richtungen)	30 G (300 m/s²) in alle Richtungen gemäß IEC60068-2-27
Verschmutzungsgrad	2
Hohe (Betrieb)	2500 Meter für die industrielle Anwendung 5000 Meter für ITE-Anwendung
Klimaklasse	3K3 gemäß EN60721
Zertifizierung und Normen	
Elektrische Ausrüstung von Maschinen	IEC60204-1 (Überspannungskategorie III)
Ausstattung von Starkstromanlagen mit elektronischen Betriebsmitteln	IEC/EN62477-1 / IEC62103
Schutzkleinspannung	PELV (EN60204), SELV (EN60950)
Elektrische Sicherheit	SIQ nach EN60950-1, EN61558-1, EN61558-2-16, EN61010-1, EN61010-2-201, IEC62103-1 EUROPE: anerkannt nach UL60950-1 und CSA C22.2 Nr. 60950-1 Prüfprotokoll und -bericht nach IEC60950-1, IEC61558-1, IEC61558-2-16, IEC61010-1, IEC61010-2-201
Industrielle Regeleinrichtungen	UL/UL gelistet nach UL508 und CSA C22.2 Nr.107.1-01, CSA nach CSA C22.2 Nr.107.1-01 (File Nr.181564)
Maritime Anwendungen	DNV GL, Umweltkategorie: C, EMC2 ABS (American Bureau for Shipping) PDA
Schutz gegen elektrischen Schlag	DIN57100-410
EC	In Konformität zur EMV-Richtlinie und Niederspannungsrichtlinie
Komponenten-Netzteil zur allgemeinen Verwendung	EN61204-3
Stoßfestigkeit	EN55005, EN55022, EN61000-6-2, EN61131-2, EN61326-1
Emission	EN5011, EN5022, EN61000-3-2, EN61000-3-3, EN61000-6-4
Sicherheit und Schutzeinrichtungen	
Überspannungsschutz gegen transiente Überspannungen	VARISTOR
Strombegrenzung bei Kurzschluss	$I_{short} = 150 \text{ % der max. Ausgangsleistung}$ (Hiccup-Modus)
Überspannungsschutz gegen interne Überspannungen	Ja
Isolationsspannung	
Eingang / Schutzleiter	4.55 kVac 2.50 kVdc
Ausgang / DC-OK*	4.54 kVac 1.50 kVdc
Ausgang / Schutzleiter	0.50 kVac 1.50 kVdc
DC OK / Schutzleiter	
Schutzart	IP20
Schutzklasse	Klasse I mit Schutzleiteranschluss

\*Empfohlene Beschaltung der DC OK und Ausgangs-Pins.

## ENGLISH

### Installation notes

#### 1. Safety instructions

- An easily accessible disconnecting device shall be provided to disconnect the unit from the mains supply for servicing.
- Switch main power off before connecting or disconnecting the device. Risk of explosion!
- If the unit is used in a manner not specified by the manufacturer, the protection provided by the equipment may be impaired.
- To guarantee sufficient convection cooling, please refer to the following instructions to ensure sufficient clearance around the device.
- Vertical Mounting: 40mm above and 20mm below the device as well as a lateral distance of 5mm to other units. In case the adjacent device is a heat source, the lateral distance will be 15mm.
- Horizontal Mounting: 40mm above and below the device as well as a lateral distance of 20mm to other units.
- The external enclosure where the unit will be installed shall meet the requirements for mechanical, electrical and fire enclosure.
- Note that the enclosure of the device can become very hot depending on the ambient temperature and load of the power supply. Risk of burns!
- The main power must be turned off before connecting or disconnecting wires to the terminals!
- Do not introduce any objects into the unit!
- Dangerous voltage present for at least 5 minutes after disconnecting all sources of power.
- The power supplies are built in units and must be installed in a cabinet or room (condensation free environment and indoor location) that is relatively free of conductive contaminants.

### CAUTION:

"FOR USE IN A CONTROLLED ENVIRONMENT".

#### 2. Device description (Fig. 1)

- (1) Input terminal block connector
- (2) Output terminal block connector
- (3) DC voltage adjustment potentiometer
- (4) DC OK LED (green)
- (5) LED „Overload“ (red)
- (6) Universal mounting rail system

(7) Gas discharge tube (on left side of housing) used for surge protection. Disconnect gas discharge tube (remove Phillips head screw) during dielectric test of > 0.9kVac or 1.3kVdc.

#### 3. Mounting and dismantling (Fig. 2, Fig. 3)

The power supply unit can be mounted on 35mm DIN rails in accordance with EN60715. For Vertical Mounting, the device should be installed with input terminal block on the bottom. For Horizontal Mounting, the device should be installed with input terminal block on the left side.

Each device is delivered ready to install.

- Tilt the unit slightly upwards and put it onto the DIN rail. Snap on the DIN rail as shown in Fig. 2.
- Push downwards until stopped.
- Press against the bottom front side for locking.
- Shake the unit slightly to ensure that it is secured.
- To uninstall, pull or slide down the latch as shown in Fig. 3. Then, slide the PSU in the opposite direction, release the latch and pull out the PSU from the rail.

#### 4. Connection

The terminal block connectors allow easy and fast wiring.

You can use flexible (stranded wire) or solid cables with the following cross sections:

##### Table 1

Refer to Fig. 1:	Stranded / Solid		Torque	
	(mm²)	(AWG)	(Kgf-cm)	(lb in)
(1)	0.82-8.4	18-8	9.3	8.1
(2)	2.1-3.3	14-12	6.3	5.4

To secure reliable and shock proof connections, the stripping length should be 7mm (see Fig. 5 (1)). Please ensure that the wires are fully inserted into the connecting terminals as shown in Fig. 5 (2). All wire strands must be fully inserted into the terminals with the screws securely fastened in order to ensure safety and maximum contact.

In accordance to EN60950 / UL60950, flexible cables require ferrules.

Use appropriate copper cables that are designed to sustain operating temperature of:  
1. 60 °C, 60 °C / 75 °C for USA  
2. At least 90 °C for Canada and IEC/EN61010-1, IEC/EN61010-2-201.


#### 4.1. Input connection (Fig. 1, Fig. 6)

For AC input connections, use L, N and PE connections on the input terminal connector (see Fig. 1(1)) to establish the 100-240Vac connection. Fig. 6 shows the connection to the various network types.

For DC input connections, the following can be done.

- L connects to + $V_e$  and N connects to - $V_e$  or
- B) L connects to - $V_e$  and N connects to + $V_e$

The unit is protected with internal fuse (not replaceable) at L pin and it has been tested and approved on 20A (UL) and 16A (IEC) branch circuits without additional protection device. An external protection device is only required if the supplying branch has an ampacity greater than above. Thus, if an external protective device is necessary, or, utilized, a minimum value of 10A B- or 6A C-characteristic breaker should be used.



The internal fuse must not be replaced by the user.  
In case of internal defect, return the unit for inspection to the manufacturer.

#### 4.2. Output connection (Fig. 1)

Use the "+" and "-" screw connections to establish the 24Vdc connection. The output provides 24Vdc. The output voltage can be adjusted from 24 to 28Vdc on the potentiometer. The green LED DC OK displays correct function of the output (Fig. 1(4)). The device has a short circuit and overload protection and an over voltage protection limited to 35Vdc.

#### 4.3. Output characteristic curve

The device functions normal under operating line and load conditions. In the event of an over load ( $I_o > 150\%$ ) the output voltage will start to droop and bounce until over load has been removed. If the loads are in short circuit, the secondary voltage will bounce and recover once the short circuit has been removed.

#### 4.4 Indicators and relay contacts (Fig. 4)

#### 4.5 Thermal behavior (Fig. 7)

In the case of ambient temperatures above +60 °C (Vertical) or +40 °C (Horizontal), the output capacity has to be reduced by 2.5% per Celsius increase in temperature. If the output capacity is not reduced when  $T_{amb} > 60^\circ\text{C}$  (Vertical) or > 40 °C (Horizontal), the device will run into thermal protection by switching off i.e. device will go in bouncing mode and will recover when ambient temperature is lowered or load is reduced as far as necessary to keep device in working condition.

## ENGLISH

### Technical data

Input (AC)	




<tbl\_r cells="2" ix

